

No.	Ref	Qty	Value	型番 (秋月電子/千石電商など)	千石電商、その他
1	C1, C2, C3, C4,	4	22u/16V PMLCAP	16MU226MD35750 5750サイズ (オプション、 C5,C6,C7,C8の代わりに)	https://akizukidenshi.com/catalog/g/gP-08058/
2	C5, C6, C7, C8, C13, C14, C15, C16, C25, C26, C27, C28, C29, C30, C31, C32, C35, C36,	18	100u/25V	UFG1E101MPM 100uF 25V Φ8mm	https://akizukidenshi.com/catalog/g/gP-05041/
3	C9, C10, C43,	3	10u/50V	UFG1H100MDM 10uF 50V Φ5mm	https://akizukidenshi.com/catalog/g/gP-04621/
4	C11, C12, C33, C34, C37, C38, C39, C40, C41, C42,	10	0.1u	GCM188L81H104K57 1608サイズ	https://akizukidenshi.com/catalog/g/gP-16143/
5	C17, C18, C19, C20,	4	10u/16V PMLCAP	16MU106MC44532 4532サイズ	https://akizukidenshi.com/catalog/g/gP-08057/
6	C21, C22, C23, C24,	4	10p	5~10pF程度 位相補償 1608 オペアンプに合わせて	https://akizukidenshi.com/catalog/g/gP-05520/
7	D1, D2,	2	1S4	1S4 40V 1A ショットキー	https://akizukidenshi.com/catalog/g/gI-16384/
8	D3,	1	LED	Φ5mm LED 好みで	https://akizukidenshi.com/catalog/c/c5mm/
10	J1, J2, J3, J4,	4	B4B-XH-A	B4B-XH-A(LF)(SN)	https://akizukidenshi.com/catalog/g/gC-12249/
11	J5,	1	TB3	B3B-XH-A(LF)(SN) またはTB111-2-3-U-1-1	https://akizukidenshi.com/catalog/g/gC-12248/ https://akizukidenshi.com/catalog/g/gP-01307/
12	J6,	1	Conn_02x02	2列2極 ピンヘッダ PH-2x2SG	https://akizukidenshi.com/catalog/g/gC-16792/
13	J7,	1	5PIN_ICD	1列5極ピンヘッダ (オプション)	https://akizukidenshi.com/catalog/g/gC-00167/
14	R1, R2, R21, (裏面) R7, R8, R9, R10	7	10	RK73B1JTDD100J 10Ω5% 1608 チップ抵抗	https://www.sengoku.co.jp/mod/sgk_cart/detail.php?code=EEHD-57F7
15	R3, R4, R5, R6,	4	470k	RK73B1JTDD474J 470Ω5% 1608 チップ抵抗	https://www.sengoku.co.jp/mod/sgk_cart/detail.php?code=EEHD-57HJ
16	R11, R12, R13, R14,	4	47_1/4W	REY25FY47Ω 47~100Ω オーディオ用抵抗	https://www.sengoku.co.jp/mod/sgk_cart/detail.php?code=3BZ3-RFGC
17	R15, R16,	2	220_1/4W	24V = 390_1W 電源電圧に応じて 22V = 330_1/2W 適切な抵抗値を 20V = 220_1/4W ご使用ください。 18V = 150_1/4W 16V = 75_1/4W	RLC25FY 220Ω https://www.sengoku.co.jp/mod/sgk_cart/detail.php?code=EEHD-5FCU
18	R17, R19,	2	22k	RK73B1JTDD223J	https://www.sengoku.co.jp/mod/sgk_cart/detail.php?code=EEHD-57GZ
19	R18, R20,	2	4.7k	RK73B1JTDD472J	https://www.sengoku.co.jp/mod/sgk_cart/detail.php?code=EEHD-57GR
20	R22,	1	1k	RK73B1JTDD102J	https://www.sengoku.co.jp/mod/sgk_cart/detail.php?code=EEHD-57GK
21	R23,	1	10k	RK73B1JTDD103J	https://www.sengoku.co.jp/mod/sgk_cart/detail.php?code=EEHD-57GX
22	U1, U2,	2	MUSES72323	MUSES72323	https://akizukidenshi.com/catalog/g/gI-15590/
23	U3, U4, U5, U6,	4	NE5534	NJM5534D	https://akizukidenshi.com/catalog/g/gI-06715/
24	U7, U8,	2	NJM7400DL1	NJM7400DL1	https://akizukidenshi.com/catalog/g/gI-09497/
25	U9,	1	L78L05	L78L05ACZ	https://akizukidenshi.com/catalog/g/gI-01250/
26	U10,	1	PIC16F18326-L_SL	ファームウェア書き込み済みマイコン	
27	VR1, VR2, VR3, VR4,	4	100k	3296W-1-104LF DCオフセット調整用 (使用OPAMPによって値が異なります)	https://akizukidenshi.com/catalog/g/gP-00922/
28	VR5, VR6,	2	RK097 B503 20k~50kΩ Bカーブ	RK0971210-F15-C0-B503	https://akizukidenshi.com/catalog/g/gP-03605/