

| Item | Qty | Reference(s) | Value | 型番 (秋月電子/千石電商) | URL |
|------|-----|--|-----------------------|--|---|
| 1 | 2 | C1, C2 | 22u_PMLCAP | 16MU226MD35750 | https://akizukidenshi.com/catalog/g/gP-08058/ |
| 2 | 7 | C3, C4, C10, C11, C14, C15, C24 | 0.1u | GRM188F11H104ZA01 | https://akizukidenshi.com/catalog/g/gP-13374/ |
| 3 | 10 | C5, C6, C8, C9, C12, C13, C20, C21, C22, | 100u/25V | UFG1E101MPM | https://akizukidenshi.com/catalog/g/gP-05041/ |
| 4 | 1 | C7 | 10u/50V | UFG1H100MDM | https://akizukidenshi.com/catalog/g/gP-04621/ |
| 5 | 2 | C16, C17 | 10u_PMLCAP | 16MU106MC44532 JFET入力OPAMPならバイパス可 | https://akizukidenshi.com/catalog/g/gP-08057/ |
| 6 | 2 | C18, C19 | 10p | CC0603N150J500 | https://akizukidenshi.com/catalog/g/gP-13312/ |
| 7 | 2 | D1, D2 | 1S4 | 1S4 | https://akizukidenshi.com/catalog/g/gI-00127/ |
| 8 | 1 | D3 | LED | Φ5mm 好きな色 | https://akizukidenshi.com/catalog/c/c5mm/ |
| 9 | 2 | J1, J2 | B4B-XH-A | B4B-XH-A 直接配線を半田付でもOK | https://akizukidenshi.com/catalog/g/gC-12249/ |
| 10 | 1 | J3 | TB3 | TB111-2-3-U-1-1 | https://akizukidenshi.com/catalog/g/gP-01307/ |
| 11 | 1 | J4, J5 | GAIN1/GAIN2 | PH-1x40SG J4/J5部に4pinヘッダ | https://akizukidenshi.com/catalog/g/gC-00167/ |
| 12 | 2 | J4, J5 | Jumper | 2228GG-BU ゲイン設定用ジャンパ | https://akizukidenshi.com/catalog/g/gP-03892/ |
| 13 | 1 | J6 | 5PIN_ICD | Debug/書込み用 | |
| 14 | 2 | R1, R2 | 220_1/4W | 24V = 470_1/2W 電源電圧に応じて 22V = 390_1/4W 適切な抵抗値を 20V = 270_1/4W ご使用ください。 18V = 220_1/4W 16V = 100_1/4W | https://akizukidenshi.com/catalog/g/gR-03359/ |
| 15 | 2 | R3, R5 | 22k_1608 | RK73B1JTDD223J | https://www.sengoku.co.jp/mod/sgk_cart/detail.php? |
| 16 | 2 | R4, R6 | 4.7k_1608 | RK73B1JTDD472J | https://www.sengoku.co.jp/mod/sgk_cart/detail.php? |
| 17 | 2 | R7, R8 | 100k_1608 | RK73B1JTDD104J | https://www.sengoku.co.jp/mod/sgk_cart/detail.php? |
| 18 | 2 | R9, R16 | 10_1608 | RK73B1JTDD100J | https://www.sengoku.co.jp/mod/sgk_cart/detail.php? |
| 19 | 2 | R11, R12 | not use | 10~22Ω程度入れても良い 1608サイズ | |
| 20 | 1 | R10 | 1k_1608 | RK73B1JTDD102J | https://www.sengoku.co.jp/mod/sgk_cart/detail.php? |
| 21 | 2 | R13, R14 | 47_1/4W | REY25FY43Ω (47Ω品切れ中) | https://www.sengoku.co.jp/mod/sgk_cart/detail.php? |
| 22 | 1 | R15 | 10k_1608 | RK73B1JTDD103J | https://www.sengoku.co.jp/mod/sgk_cart/detail.php? |
| 23 | 1 | RV1 | RK0971210-F15-C0-B503 | RK0971210-F15-C0-B503 | https://akizukidenshi.com/catalog/g/gP-03605/ |
| 24 | 2 | RV2, RV3 | VR100k | 3296W-1-104LF DCオフセット調整用 (使用OPAMPによって値が異なります) | https://akizukidenshi.com/catalog/g/gP-00922/ |
| 25 | 2 | U1, U2 | NJM7400DL1 | NJM7400DL1 | https://akizukidenshi.com/catalog/g/gI-09497/ |
| 26 | 1 | U3 | MUSES72323 | MUSES72323 | https://akizukidenshi.com/catalog/g/gI-15590/ |
| 27 | 1 | U4 | L78L05_TO92 | L78L05ACZ | https://akizukidenshi.com/catalog/g/gI-01250/ |
| 28 | 2 | U5, U6 | NE5534 | NJM5534D | https://akizukidenshi.com/catalog/g/gI-06715/ |
| 29 | 1 | U7 | PIC16F18326-I_SL | ファームウェア書込み済みマイコン | |
| 30 | 1 | 裏面 CC1 | 10uF/50V | UFG1H100MDM OLED表示機を付ける場合に裏面に増設 | https://akizukidenshi.com/catalog/g/gP-04621/ |

※) 黄枠の部品は付録します。