

Item	Qty	Reference(s)	Value	お勧め部品	URL
1	2	C1, C2	100p	WIMA FKP2 63V 100pF	<a href="https://www.sengoku.co.jp/mod/sgk_cart/detail.php?">https://www.sengoku.co.jp/mod/sgk_cart/detail.php?</a>
2	11	C3, C4, C5, C6, C9, C10, C17, C20, C21, C24, C25	100u/25V	Φ8mm電解コンデンサ ニチコン UFG1E101MPM C24,C25は330~1000uFを推奨	<a href="https://akizukidenshi.com/catalog/g/gP-05041/">https://akizukidenshi.com/catalog/g/gP-05041/</a>
3	6	C11, C12, C13, C14, C15, C16	10p	33pF~47pF 位相補償 1608もOK (10pFでは発振のおそれ)	<a href="https://akizukidenshi.com/catalog/g/gP-05439/">https://akizukidenshi.com/catalog/g/gP-05439/</a>
4	3	C18, C22, C23	10u/16V_PMLCAP	16MU106MC44532	<a href="https://akizukidenshi.com/catalog/g/gP-08057/">https://akizukidenshi.com/catalog/g/gP-08057/</a>
5	1	C19	0.1u	1608チップ コンデンサ	<a href="https://akizukidenshi.com/catalog/g/gP-13374/">https://akizukidenshi.com/catalog/g/gP-13374/</a>
6	5	D1, D2, D4, D5, D6	1N4148	1N4148	<a href="https://akizukidenshi.com/catalog/g/gI-00941/">https://akizukidenshi.com/catalog/g/gI-00941/</a>
7	1	D3	SB340LS	逆電圧保護SBD 1A20V以上	<a href="https://akizukidenshi.com/catalog/g/gI-07788/">https://akizukidenshi.com/catalog/g/gI-07788/</a>
8	1	J1	TB2	未使用	
9	1	J2	Conn_02x05_Odd_Even	PH-2x10RG を切って使う 8pinを抜き取る	<a href="https://akizukidenshi.com/catalog/g/gC-10903/">https://akizukidenshi.com/catalog/g/gC-10903/</a>
10	1	J4	NBA1-24-001	4.4mm5極ジャック	<a href="https://www.sengoku.co.jp/mod/sgk_cart/detail.php?">https://www.sengoku.co.jp/mod/sgk_cart/detail.php?</a>
11	1	J5	MJ-188LPD-8C	6.3mmジャック	<a href="https://akizukidenshi.com/catalog/g/gC-13880/">https://akizukidenshi.com/catalog/g/gC-13880/</a>
12	1	J6	SJ-3568N	3.5mmジャック	<a href="https://www.digikey.jp/product-detail/ja/cui-devices/">https://www.digikey.jp/product-detail/ja/cui-devices/</a>
13	3	L1, L2, L3	941H-2C-12D	12Vリレー 高感度コイル品	<a href="https://akizukidenshi.com/catalog/g/gP-01228/">https://akizukidenshi.com/catalog/g/gP-01228/</a>
14	1	LED1	LED_BLUE	青,純緑などVF=3.5VのLED	<a href="https://akizukidenshi.com/catalog/g/gI-01267/">https://akizukidenshi.com/catalog/g/gI-01267/</a>
15	13	Q1, Q3, Q5, Q7, Q9, Q10, Q13, Q14, Q17, Q18, Q21, Q22, Q26	2SC2655L	50V2A NPNトランジスタ	<a href="https://akizukidenshi.com/catalog/g/gI-08746/">https://akizukidenshi.com/catalog/g/gI-08746/</a>
16	13	Q2, Q4, Q6, Q8, Q11, Q12, Q15, Q16, Q19, Q20, Q23, Q24, Q25	2SA1020L	50V2A PNPトランジスタ	<a href="https://akizukidenshi.com/catalog/g/gI-08745/">https://akizukidenshi.com/catalog/g/gI-08745/</a>
17	12	R1, R2, R5, R6, R7, R8, R10, R12, R17, R18, R19, R20	3.3k	金属皮膜抵抗 1/4W 1% MF1/4CC3301F	<a href="https://akizukidenshi.com/catalog/g/gR-03387/">https://akizukidenshi.com/catalog/g/gR-03387/</a>
18	2	R3, R4	680	金属皮膜抵抗 1/4W 1% MF1/4CC6800F	<a href="https://akizukidenshi.com/catalog/g/gR-03371/">https://akizukidenshi.com/catalog/g/gR-03371/</a>
19	8	R9, R11, R13, R14, R15, R16, R34, R36	1k	金属皮膜抵抗 1/4W 1% MF1/4CC1001F	<a href="https://akizukidenshi.com/catalog/g/gR-03375/">https://akizukidenshi.com/catalog/g/gR-03375/</a>
20	8	R21, R22, R23, R24, R25, R26, R27, R28	390	金属皮膜抵抗 1/4W 1% MF1/4CC3900F	<a href="https://akizukidenshi.com/catalog/g/gR-03365/">https://akizukidenshi.com/catalog/g/gR-03365/</a>
21	4	R29, R30, R31, R32	1_2W	MPC78-1ohmJ	<a href="https://akizukidenshi.com/catalog/g/gR-10696/">https://akizukidenshi.com/catalog/g/gR-10696/</a>
22	1	R33	100k	金属皮膜抵抗 1/4W 1% MF1/4CC1003F	<a href="https://akizukidenshi.com/catalog/g/gR-03505/">https://akizukidenshi.com/catalog/g/gR-03505/</a>
23	1	R35	100	金属皮膜抵抗 1/4W 1% MF1/4CC1000F	<a href="https://akizukidenshi.com/catalog/g/gR-03351/">https://akizukidenshi.com/catalog/g/gR-03351/</a>
24	2	R37, R38	AMO	アモビーズ AB3x2x3DY をリード線に通す	<a href="https://akizukidenshi.com/catalog/g/gP-12896/">https://akizukidenshi.com/catalog/g/gP-12896/</a>
25	2	R39, R40	470	金属皮膜抵抗 1/4W 1% MF1/4CC4700F	<a href="https://akizukidenshi.com/catalog/g/gR-03367/">https://akizukidenshi.com/catalog/g/gR-03367/</a>
26	1	SW1	2MS1-T1-B4-M7-Q-E-S	サイド型トグルスイッチ	<a href="https://akizukidenshi.com/catalog/g/gP-13796/">https://akizukidenshi.com/catalog/g/gP-13796/</a>
27	3	U1, U3, U4	NE5532	2回路入りOPAMP 好みの物をご使用ください	<a href="https://akizukidenshi.com/catalog/g/gI-00068/">https://akizukidenshi.com/catalog/g/gI-00068/</a>
28	1	U5	TLP241A	フォトカプラ MOS	<a href="https://akizukidenshi.com/catalog/g/gI-11516/">https://akizukidenshi.com/catalog/g/gI-11516/</a>
29	1	U6	MIWI06-24D05	±5V出力DCDC	<a href="https://akizukidenshi.com/catalog/g/gM-06536/">https://akizukidenshi.com/catalog/g/gM-06536/</a>

※黄枠の部品は付録します。

※緑枠とR36は、HDAudio接続にてPCへ組み込まない場合は必要ありません。